

Cast Solid Bronze Safe Touch[™] 100 **SAFE TOUCH**


PROJECT:
TYPE:
SOURCE:
NOTES:

SPECIFICATIONS IK10 IP68 (€ CUDUS LISTER)

LED Chip	Cree CXA 1830 field replaceable LED board
Luminaire Output	2700 Lumens @ 700mA (26 watts) delivered from luminaire with unobstructed beam.
Lumens Per Watt	100 Lumens minimum @ 26 watts delivered from luminaire with unobstructed beam
CRI (3000K)	80 Standard, 90+ Optional
Colour Temperatures	2700K, 3000K, 4000K
Beam Angles	13, 20, 25, 34
Ingress Protection	IP68 *not for use in pool or ponds
Warranty	Electronics = 5 years Body Cast Solid Bronze = 25 years
Standards	BS/EN 60598.2.2


CE

cUL 1598, CSA C22.2 No. 250.0



PRODUCT CONFIGURATION

Please fill in appropriate codes into boxes provided



SERIES REMOTE:

Constant current driver (included) individual fixtures require 37vdc @ 700mA maximum. 0-10 volt dimming.

RETRO 110-277vac DRIVER:

Constant current driver (included).

Input: 120, 240, 277 volts. Output: 30 watts total 37vdc @ 700mA. 0-10 volt dimming.

24VDC DRIVER:

Input: 24vdc.

Output: 36vdc @ 700mA constant current (non dimming). Note: not for USA. ADDITIONAL COMMENTS:



LUMINAIRE CONSTRUCTION

CNC machined sand cast silicon bronze.

Flanges:

CNC machined from either Solid Bronze 260mm x 6mm (101/4" x 1/4") 316 Stainless Steel 260mm x 6mm (101/4" x

All fixings are made form 316 Stainless Steel.

Step Lens:

12mm (1/2") Extra clear, low iron, shatter resistant glass. Anti Slip option available. Lifetime warranty.

Silicone, iron impregnated 220°C (428°F).

Cable:

Water resistant rubber.

Adjustability:

The gimbal is fully adjustable, allowing 360° rotation and 0-20° elevation.

Mounting:

The ST100 is available with a spun 316 stainless steel mounting canister for casting into the ground concrete. Maximum drive over speed 10 kp/h (6mp/h) with a maximum load rating of 2000kgs (4400lbs).

Luminaire Weight:

6kg (13lb 4oz)

ACCESSORIES










Glare Shield

BEAM ANGLES


High efficiency Reflectors. Feild replaceable

IES files available for download: hunzalighting.com/downloads



WIRING GUIDE

Available for download: hunzalighting.com/downloads



Diagrams are a guide only, wire colours and polarity may change depending on fixture and country

